

To: Digital Watchdog® Customers
Date: October 16, 2018
Re: How to Add a DVR to a Digital Spot™ Monitor Using an RTSP URL

How to Add a DVR to a Digital Spot™ Monitor Using an RTSP URL

DW®'s Spot Monitoring Module allows you to add a live monitoring screen from any VMAX® A1™ DVR, VMAX® AHD™ DVR, or VMAX® IP Plus™ NVR. To add a live stream from a VMAX® A1™, you simply have to manually add the DVR's RTSP URL. The steps below can be used to add any other recorder that supports RTSP communications.

To add a channel using an RTSP URL:

1. In the Spot Monitoring Module, right click anywhere on the screen and go to the Main Menu.
2. Go to MONITORING ! REGISTRATIONS



3. Click on the "ADD CAMERAS MANUALLY" button.



[Schedule a demo today >](#)

Learn how DW will increase your profitability.

866.446.3595

sales@dwcc.tv

www.digital-watchdog.com

4. Enter the DVR's ID & PWD
5. Select which channel you want to add to the Spot Monitoring Module.
6. Under Protocol, select RTSP instead of ONVIF (default).
7. Enter the DVR's model name (opEonal).
8. Enter the DVR's brand name (opEonal).
9. Enter the DVR's RTSP URL. Please note to enter the URL only on the first RTSP field.
 - a. The VMAX A1's RTSP URL should be in the following format:
rtsp://xxx.xxx.xxx.xxx:port/rtsp/unicast/live/profile-xFor example: rtsp://192.168.1.100:80/rtsp/unicast/live/profile-1
 - b. Enter the DVR's IP address: xxx.xxx.xxx.xxx.
 - c. Port: Use the DVR's web port (default value is 80).
 - d. Profile-x: Enter the DVR's channel number you want to add.
10. Press "APPLY" to save the changes.




For more information or technical support

Digital Watchdog Customer Service
Toll free: 866.446.3595
customerservice@dwcc.tv

Schedule a demo today >

Learn how DW will increase your profitability.



www.digital-watchdog.com